

# MICRO-OHM METER

Model: *indi* 953



## Specification:

<b>Display</b>	1999 Count LED
<b>Range</b>	1 micro ohms to 19.99 K ohms in 8 full scale ranges of 0-1999 micro ohms, 0-19.99 milli ohms, 0-199.9 milli ohms, 0-1999 milli ohms, 0-19.99 ohms, 0-199.9 ohms, 0-1999 ohms and 0-19.99 K ohms
<b>Resolution</b>	1 micro ohms in 1999 micro ohms range, 0.01milli ohms 19.99 milli ohms range, 0.1milli ohms in 199.9 milli ohms range, 1 milli ohms in 1999 milli ohms range, 0.01 ohms in 19.99 ohms range, 0.1 ohms in 199.9 ohms range, 1 ohm in 1999 ohms in 19.99 K ohms range
<b>Accuracy</b>	± 0.2 % ± 2 least counts in all ranges except in 200 milli ohms, 20 milli ohms and 2000 micro ohms ranges. ±0.5% ± 3 least count in 200 milli ohms, 20 milli ohms and 2000 micro ohms ranges
<b>Test Current</b>	1 Amp DC in 1999 micro ohms, 19.99 milli ohms, 199.9 milli ohms and 1999 milli ohms ranges. 0.1 amp DC in 19.99 ohms range, 10 milli amp DC in 199.9 ohms range, 1 milli amp DC in ohms range, 0.1 milli amp DC in 19.99 K ohms range
<b>Measurement System</b>	4 Terminal
<b>Stability</b>	25 PPM / °C
<b>Over Range</b>	1 or -1 is displayed
<b>Supply</b>	230±10%VAC
<b>Cabinet Size</b>	225 (L) x 200 (D) x 85 (W)

## Source 1 INSTRUMENTS

Plot No. L/715/10, 40 Shed Area, GIDC, Vapi – 396195. Gujarat. India.

Tel: (0260) 325 1066 Fax: (0260) 2401654 Mob: 93770 29027 / 98244 64050

Email: [sales@source1in.com](mailto:sales@source1in.com) [source1in@indiatimes.com](mailto:source1in@indiatimes.com) URL: [www.source1in.com](http://www.source1in.com)

Branch Offices: Rajkot Baroda Surat Ahmedabad Chandigarh Nashik Pune Coimbatore

**3 YEAR\***  
**REPLACEMENT**  
**WARRANTY**