

# PROFILE CONTROLLER

Model: *indi* 6358



## Specification:

<b>Display</b>	PV: Digital L.E.D / SV: LCD Backlight
<b>Input</b>	Universal-input (T/C: 13 kinds, R.T.D: 2 kinds, Voltage: 3 kinds)
<b>Function</b>	Retransmission output, Input correction, Auto/Manual output, Direct/Reverse action, Alarm output (Relay), Time signals (Transistor), Constant Value control, Heating/Cooling, 4 Zone PID, 5 Time Signals
<b>Setting &amp; Display Accuracy</b>	±0.1% F.S.
<b>Control output</b>	Universal-output: Relay, SSR, Current
<b>Control action</b>	P.I.D or ON/OFF
<b>Alarm</b>	2 Alarm output
<b>Communication</b>	RS 485/422 (Optional)
<b>Setting</b>	By Up/Down Key on the front
<b>Memory</b>	1 or 0.1% (According to input range)
<b>Memory protection</b>	Semi permanent
<b>External control</b>	Run, Reset, Pattern, Hold
<b>Number of pattern</b>	30
<b>Number of segment</b>	300
<b>Number of pattern segment</b>	30
<b>Operation</b>	1 ~ 99 times or limitless
<b>Program inclination</b>	Hour, Minute
<b>Sampling cycle</b>	250 ms
<b>Operating Supply</b>	100 ~ 240VAC (50/60Hz)
<b>Power consumption</b>	Max. 10VA (except communication)
<b>Ambient Temp. &amp; Humidity</b>	0 ~ 50°C (Between primary and ground), 20 ~ 90% RH
<b>Dimensions</b>	96(W)×96(H)×100(D) mm

## Source 1 INSTRUMENTS

Plot No. L/715/10, 40 Shed Area, GIDC, Vapi – 396195. Gujarat. India.

Tel: (0260) 325 1066 Fax: (0260) 2401654 Mob: 93770 29027 / 98244 64050

Email: [sales@source1in.com](mailto:sales@source1in.com) [source1in@indiatimes.com](mailto:source1in@indiatimes.com) URL: [www.source1in.com](http://www.source1in.com)

Branch Offices: Raikot Baroda Surat Ahmedabad Chandigarh Nashik Pune Coimbatore

**1 YEAR  
REPLACEMENT  
WARRANTY**