



DIGITAL VACUUM GAUGE		Model: <i>indi</i> 6368
Specification:		
Display	Full Icon LCD	
Vacuum Range	0 – 12000 microns (0 – 1600 Pascals)	
Sensor	Thermistor	
Accuracy	10% of reading±10dgts	
Unit Selection	microns, mbar, psi, inHg, Pascals, Torr, mTorr	
Display Updates	0.5 seconds	
Connection	¼” NPT Male	
Power Off	10 minutes Auto when vacuum above 12000 microns	
Operating Supply	9V Battery	
Sensor	Cleanable	
Hanging Hook	Provided	
Over Pressure	300 psi	
Cabinet Size	5” x 2.5”	
Carrying Case	Provided	

DIGITAL VACUUM GAUGE		Model: <i>indi</i> 6367
Specification:		
DISPLAY	4 ½ Digit LCD	
Range	760.0 to 000.1 mmHg. (TORR) Absolute / 1014.0 to 000.1 mBar Absolute or 000.0 to 760.0 mmHg. Gauge / 000.0 to 1014.00 mBar	
RESOLUTION	0.1	
ACCURACY	+/- 0.25%	
UNIT SELECTION	As required	
POWER SUPPLY	24 Volts D.C. / 230 V.A.C. Power Adaptor	
SENSOR	Built In Imported Stainless Steel Sensor with S.S. 316 Wetted Parts	
CONNECTION	Standard 3/8” S.S. Threaded End Connection or as required	
ENCLOSURE	IP 66 Enclosure (weather proof) ABS	
SIZE	120 x 80 x 85 mm. (L x B x H)	

<p>Source 1 INSTRUMENTS</p> <p>Plot No. L/715/10, 40 Shed Area, GIDC, Vapi – 396195. Gujarat. India.</p> <p>Tel: (0260) 325 1066 Fax: (0260) 2401654 Mob: 93770 29027 / 98244 64050</p> <p>Email: sales@source1in.com source1in@indiatimes.com URL: www.source1in.com</p> <p>Branch Offices: Rajkot Baroda Surat Ahmedabad Chandigarh Nashik Pune Coimbatore</p>	<p>1 YEAR REPLACEMENT WARRANTY</p>
-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	---------------------------------------------------